

RIBM2401SB

LED ON = RELAY ACTIVATED

Bulletin B526 • 393017B

COIL RATINGS

INPUT ISOLATED FROM OUTPUT

47 mA @ 30 Vdc

83 mA @ 24 Vac, 50-60 Hz

47 mA @ 120 Vac, 50-60 Hz

COIL

Comm

24Vac/dc

120Vac

SIGNALING



LISTED
13CY
15M6

TYPE F, G, EM

For use with
Smoke Control System
General Signaling
Equip. NM

**Functional
Devices, Inc.**



www.functionaldevices.com

N/O



N/C



Connect Yellow Jumper Wire
to N/O or N/C

Functional Devices, Inc.

310 South Union Street

Russiaville, IN 46979

Phone: (765)883-5538

Fax: (765)883-7505

CONTACT RATINGS

20A Resistive @ 277 Vac

1 HP @ 120 Vac

2 HP @ 277 Vac

20 A Ballast N/O @ 277 Vac

10 A Ballast N/C @ 277 Vac

10 A Tungsten N/O @ 120 Vac

770 VA Pilot @ 120 Vac

1110 VA Pilot @ 277 Vac

CONTACTS

Relay Contacts



Not Used

